

## Connect any Ethernet-equipped device to a Wireless Network



The versatile Wireless Ethernet Bridge can make any wired Ethernet-equipped device a part of your wireless network. At home, use the Wireless Ethernet Bridge to connect game consoles, set-top boxes, or computers into your wireless network to share your high-speed network connection. In the office, convert your Ethernet-wired printer, scanner, camera, notebook or desktop into a wireless networked device.

It's completely driver-free, so it works on any platform and under any operating system! Since there are no drivers to load, setup is a snap – just plug it into your device and configure the network settings through your web browser.

You can also use the Wireless Ethernet Bridge as a kind of "cable-less cable" to connect remote areas together. Maybe Shipping is all the way across the warehouse from Receiving. Or maybe you want to set up a home office in your detached garage. With a Wireless Ethernet Bridge in the garage, and another one (or a Wireless Access Point) in the house, you're connected – with no cabling hassle.

Converts wired-Ethernet devices to wireless network connectivity

Works without drivers on Macintosh®, Windows®, PlayStation®2, Xbox™, Linux®, network printers – anything with an Ethernet port!

Provides wireless, cable-free bridging between remote workgroups

Easily configurable through your web browser

# Wireless-B Ethernet Bridge

Wireless

Product Data

# Wireless-B Ethernet Bridge

## Features

- Interoperable with IEEE 802.11b (DSSS) 2.4GHz - Compliant Equipment
- No Additional Drivers Are Needed
- Up to 11 Mbps High-Speed Transfer Rate
- Dynamically Shifts between 11, 5.5, 2, and 1 Mbps for Maximum Adaptability
- Up to 128-bit WEP Encryption
- Easy to Install and Set up
- 2-Year Warranty

## Specifications

Model	WET11
Standards	IEEE 802.11b, IEEE 802.3
Ports	One 10BaseT RJ-45 port, Power port
Buttons	MDI/MDI-X slide switch, Reset
Cabling Type	Category 5 or better
LEDs	Power, LAN, WLAN, Diag
Peak Gain of Antenna	5 dBi
Transmit Power	15 dBm @ Normal Temperature
Receive Sensitivity	-85 dBm
Security	WEP 64/128 bits

## Environmental

Dimensions (W x H x D)	120 mm x 31 mm x 94 mm (4,72" x 1,22" x 3,70")
Unit Weight	0,2 kg (7,06 oz.)
Power	External, DC 5 V
Certifications	FCC, CE, IC-03, Wi-Fi
Operating Temp.	0°F to 40°C (32°F to 104°F)
Storage Temp.	-20°F to 70°C (-4°F to 128°F)
Operating Humidity	10% to 85% Non-Condensing
Storage Humidity	5% to 90% Non-Condensing
Warranty	2-Year Warranty

### Linksys

Web: <http://www.linksys.com/international>

Linksys products are available in more than 50 countries, supported by 12 Linksys Regional Offices throughout the world. For a complete list of local Linksys Sales and Technical Support contacts, visit our Worldwide Web Site at [www.linksys.com/international](http://www.linksys.com/international).

### Minimum Requirements

- Microsoft Windows 98SE, 2000, Me or XP (for Setup Wizard configuration purposes)
- CD-ROM Drive
- Internet Explorer 4.0 or higher, or Netscape Navigator 4.0 or higher
- Network Adapter with Ethernet (UTP CAT 5) Cabling and TCP/IP Protocol Installed per PC or 802.11g or 802.11b Wireless Adapter with TCP/IP Protocol Installed

### Package Contents

- Wireless-B Ethernet Bridge
- Quick Installation Guide
- Setup CD-ROM
- User's Guide on CD
- Detachable Antenna
- Power Adapter
- Network Cable

Specifications are subject to change without notice. Linksys is a registered trademark or trademark of Cisco Systems, Inc. and/or its affiliates in the U.S. and certain other countries. Copyright © 2003 Cisco Systems, Inc. All rights reserved. Other brands and product names are trademarks or registered trademarks of their respective holders.