



Package Contents

- Wireless-B USB Network Adapter
- USB Cable
- Wall Mount
- Setup CD-ROM with User Guide
- Quick Installation
- Registration Card

2.4GHz
802.11b

Wireless-B
USB Network Adapter

Quick Installation for Windows 98SE, Me, and 2000



1 Install the Wireless-B USB Network Adapter's Software

IMPORTANT: Windows 98SE, Me, and 2000 users do not connect the Adapter to Your PC until instructed to do so or the setup will not work.

The Wireless-B USB Network Adapter Setup Wizard will guide you through the software installation procedure for Windows 98SE, Me, and 2000.

A Insert the Setup CD-ROM into your computer's CD-ROM drive. The Setup Wizard should run automatically, and the *Welcome* screen should appear. If it does not, click **Start** and choose **Run**. In the field that appears, enter **D:\setup.exe** (if "D" is the letter of your CD-ROM drive).

B To install the Adapter, click **Install**.

C After reading the License Agreement, click **Next** to accept the agreement.

D The Setup Wizard will ask you to choose a network mode. Click the **Infrastructure Mode** radio button if you want your wireless computers to communicate with computers on your wired network using a wireless access point. Click the **Ad-Hoc Mode** radio button if you want multiple wireless computers to communicate directly with each other.



In the *SSID* field, enter the SSID or name of your wireless network. The SSID must be identical for all devices in your network. The default is **linksys**.

Then click **Next**.

E If you chose Infrastructure Mode, go to step F.

If you chose Ad-Hoc Mode, select the channel your network uses. Then click **Next**.

F If your network uses a wireless security feature called Wired Equivalent Privacy (WEP) encryption, then select **64-bit** or **128-bit** from the *WEP* drop-down menu. To automatically generate the WEP key, enter your passphrase. To manually enter the WEP key, leave the *Passphrase* field blank and enter the WEP key in the *WEP Key* field. Click **Next**.

If your network doesn't use WEP encryption, select **Disabled** and click **Next**.

G Review your settings before the Setup Wizard starts to copy files. Click **Next** to save these settings, or click **Back** to change any settings.



2 Connect the Wireless-B USB Network Adapter

H If you are using Windows 2000, you may see a Windows Digital Signature warning. The Adapter has been tested and found to work with Windows, so click **Yes** to continue.

I When the *Congratulations* screen appears, click **Exit**.

J Reboot your computer if Windows asks you to do so.



A The Adapter comes with the USB cable you will use to connect the Adapter to your PC.

Connect one end of the included USB cable to the USB port of the Adapter.

B Connect the other end of the USB cable to one of the USB ports on your computer.

The Power LED should light up when the Adapter is plugged in.

C If you are using Windows 2000, you may see a Windows Digital Signature warning. The Adapter has been tested and found to work with Windows, so click **Yes** to continue.

D Raise the antenna. Make sure the antenna is positioned straight up into the air, at a 90° angle from the Adapter. This will ensure optimum wireless operating range and performance.



E After the Adapter is installed, the Wireless Network Monitor icon will appear in the system tray at the bottom right-hand corner of your screen.

Double-click the icon if you want to check the wireless connection, search for available wireless networks, or make additional configuration changes.

Congratulations! The installation of the Wireless-B USB Network Adapter is complete.



LINKSYS[®]
A Division of Cisco Systems, Inc.

For additional information or troubleshooting help, refer to the User Guide on the Setup CD-ROM. You can also call or e-mail for further support.

24-hour Technical Support
800-326-7114
(toll-free from US or Canada)

E-mail Support
support@linksys.com

Website
<http://www.linksys.com> or
<http://support.linksys.com>

RMA (Return Merchandise Authorization)
<http://www.linksys.com/support>

FTP Site
<ftp://ftp.linksys.com>

Sales Information
800-546-5797 (800-LINKSYS)

Linksys is a registered trademark or trademark of Cisco Systems, Inc. and/or its affiliates in the U.S. and certain other countries. Copyright © 2004 Cisco Systems, Inc. All rights reserved.