



**Package Contents**

- 10/100/1000 Gigabit Network Adapter
- User Guide CD-ROM
- Quick Installation
- Registration Card

# 10/100/1000 Gigabit Network Adapter



## Quick Installation

Model No. **EG1032**



# 1 Installing the Adapter

Before installing the Adapter's Drivers, you must physically install the Adapter.

- A** Power off your PC and any peripheral equipment attached to it. Unplug your PC's power cord.
- B** Open your PC's case, and locate an available PCI slot on the motherboard. Check with your computer manufacturer if you need instructions.
- C** Remove the metal PCI slot cover on the back of the PC.
- D** Insert the Adapter into the PCI slot. Make sure that all the pins are touching the slot's contacts. You may have to apply a bit of pressure to slide the Adapter all the way in.
- E** After the Adapter is set firmly in place, secure its fastening tab to your PC's chassis with a mounting screw. Then, close your PC's case.
- F** Connect one end of the Ethernet network cable to the RJ-45 port of the Adapter. (Category 5e or better Ethernet network cabling is required for Gigabit transmission speeds.)



D



E



F

- G** Connect the other end of the Ethernet network cable to your network's Gigabit switch port.

Reconnect your PC's power cord, and then power on your computer.

## 2

## Installing the Windows XP Driver

After physically installing the Adapter in your computer, follow these instructions to install the driver required for Windows XP.

**A** Power on your computer. Make sure you have administrative rights on your computer; otherwise you cannot install the driver.

**B** Windows XP will automatically detect the presence of the Adapter in your computer. Insert the Driver CD into your computer's CD-ROM drive.

**C** On the *Welcome* screen of the Found New Hardware Wizard, select **Install from a list or specific location (Advanced)**, and click the **Next** button.

**D** After selecting **Search for the best driver in these locations** on the screen that appears, choose **Include this location in the search**, and enter **D:\driver\WinXP** in the field provided (if "D" is the letter of your CD-Rom drive). Then, click the **Next** button.



C



D

**E** A screen may appear informing you that the software has not passed Windows Logo testing. The software does work with Windows XP. Click the **Continue Anyway** button.

**F** When Windows XP has finished installing the driver, the *Completing the Found New Hardware Wizard* screen will appear. Click the **Finish** button.

**G** Driver installation is complete. If you want to configure the Adapter, refer to the chapter in the User Guide for configuration under Windows XP.



E



F

**LINKSYS**<sup>®</sup>

A Division of Cisco Systems, Inc.

For additional information or troubleshooting help, refer to the User Guide on the Setup CD-ROM. You can also call or email for further support.

**24-hour Technical Support**  
800-326-7114  
(toll-free from US or Canada)

**E-mail Support**  
support@linksys.com

**Website**  
<http://www.linksys.com> or  
<http://support.linksys.com>

**RMA (Return Merchandise Authorization)**  
<http://www.linksys.com/support>

**FTP Site**  
<ftp://ftp.linksys.com>

**Sales Information**  
800-546-5797 (800-LINKSYS)

Linksys is a registered trademark or trademark of Cisco Systems, Inc. and/or its affiliates in the U.S. and certain other countries. Copyright © 2003 Cisco Systems, Inc. All rights reserved.

EG1032\_v3-Q1-50406 KL